

2012 International Building Code

Errata

(Portions of text and tables not shown are unaffected by the errata)

THIRD PRINTING (Updated June 7, 2013)

CHAPTER 30 ELEVATORS AND CONVEYING SYSTEMS

3007.7 Fire service access elevator lobby. The fire service access elevator shall open into a fire service access elevator lobby in accordance with Sections 3007.7.1 through 3007.7.5.

Exception: Where a fire service access elevator has two entrances onto a floor, the second entrance shall be permitted to open into an elevator lobby in accordance with Section ~~708.14.4~~ 713.14.1.

2012 International Building Code

Errata

(Portions of text and tables not shown are unaffected by the errata)

SECOND PRINTING (Updated May 23, 2012)

CHAPTER 30 ELEVATORS AND CONVEYING SYSTEMS

3001.3 Accessibility. Passenger elevators required to be accessible or serve as part of an *accessible means of egress* shall comply with Section ~~1107~~ 1007 and 1109.7.

3006.5 Shunt trip. Where elevator hoistways or elevator machine rooms containing elevator control equipment are protected with automatic sprinklers, a means installed in accordance with NFPA 72, Section 21.4 ~~6-16.4~~, ~~Elevator Shutdown~~, shall be provided to disconnect automatically the main line power supply to the affected elevator prior to the application of water. This means shall not be self-resetting. The activation of automatic sprinklers outside the hoistway or machine room shall not disconnect the main line power supply.

3008.9.1 Protection of wiring or cables. Wires or cables that are located outside of the elevator hoistway and machine room and that provide normal or standby power, control signals, communication with the car, lighting, heating, air conditioning, *ventilation* and fire-detecting systems to ~~fire service access~~ occupant evacuation elevators shall be protected by construction having a *fire-resistance rating* of not less than 2 hours, or shall be circuit integrity cable having a *fire-resistance rating* of not less than 2 hours.

Exception: Wiring and cables to control signals are not required to be protected provided that wiring and cables do not serve Phase II emergency in-car operations.

3008.10 Emergency voice/alarm communication system. The building shall be provided with an *emergency voice/alarm communication system*. The *emergency voice/alarm communication system* shall be accessible to the fire department. The system shall be provided in accordance with Section ~~907.2-12.2~~ 907.5.2.2.